

[BLUETTI P090D External Battery Connection Cable for B230/B300](#) P090D To DC7909 ▼ £89.00 ~~£99.00~~

[BLUETTI RV CABLE 12V](#) AC200Max-12V/30A RV Cab ▼ £29.99

[BLUETTI AC Adapter](#) T500+DC7909-XT90 ▼ £179.00

Features

Tech Specs

Specifications

BATTERY INFO

Capacity: 2048Wh (51.2V,40Ah)

Cell Chemistry: LiFePO4 (Lithium Iron Phosphate)

Lifecycle: 3,500+ Cycles to 80% Original Capacity

Shelf-life: Recharge to 80% Every 3-6 Months

Management System: MPPT Controller, BMS, etc

OUTPUT

AC Output: 4 x 220V-240V,2200W In Total

Inverter Type: Pure Sine Wave

Surge Power: 4800W

USB-C Port: 2 x 5V/3A USB-A
2 x 18W USB-A

12V DC Outlets: 1 x 12V/30A (RV Outlet)
1 x 12V (Car Outlet)
2 x 12V DC 5521 (5.5mm Outlet)
*All Regulated.

Wireless Charging Pad: 2 x 15W Max. (For Each)

INPUT

AC Adapter Input: 400W.

Solar Input:	900W Max.OCV 10-145VDC, 15A
Car Input:	12/24V from Cigarette Lighter Port
Max Input:	1,300W, with AC+Solar Input

RECHARGE TIMES

AC Adapter (400W):	≈5.5~6 Hours
Solar (900W):	≈3~3.5 Hours (With prime sunshine, ideal orientation and low temperature)
12V/24V Car Outlet (100W/200W):	≈10 or 20 Hours
AC Adapter + Solar (1300W):	≈2.0~2.5 Hours (With prime sunshine, ideal orientation and low temperature)
Dual AC Adapters (800W):	≈3~3.5 Hours (<u>Extra adapter is REQUIRED</u>)

GENERAL

Scalability:	Expandable w/ Up to 2 x B230 or 2 x B300
Pass-through Charging:	Yes
Weight:	61.9lbs (28.1kg)
Dimensions (LxWxD):	16.5 x 11 x 15.2 in (42 x 28 x 38.65cm)
Operating Usage Temperature:	-4-104°F (-20-40°C)
Storage Temperature:	14-113°F (-10-45°C)
Certification:	UL, CEC, DOE, FCC, CA Prop 65
Warranty:	24 Months (Learn more about BLUETTI warranty policy)



In The Box

AC200 Max

weight: 28.1Kg/61.9lbs

15.2inch
386.5mm



16.5inch
420mm

11inch
280mm





AC200Max power Station



T400 AC Adapter & Cable




PV Charging Cable (XT90-MC4)



Car Charging Cable (XT90)



XT-90 Aviation Cable



Certificate of QC PASS



User Manual



Warranty Card

BLUETTI AC200MAX EXPANDABLE POWER STATION | 2,200W 2,048WH MANUAL

[Download Now](#)