

13kVA MGM PREMIUM PORTABLE GENSET



ENDRESS 

Power Generators

ESE 1306 DHS-GT ES *

Art. no.: 230029

Availability: active product

Fittings:

HONDA OHV engine, Starting battery 12V, Larger tank volume for longer operation, Tank level indicator - optical, Automatic low oil shut-off, Alternator overload protection, Alternator with Low Distortion Device for clear voltage, Compound regulated alternator at 400V, * Does not conform to EU noise directive 2000/14/EG

Technical data

Nominal current 1~	16,0 A 1~
Output 3000 RPM	14,2 kW
Displacement	688 ccm
Number of cylinders	2
Engine type	Honda GX630
Frequency	50 Hz
Protection class	IP23
Power factor cos (phi)	0,8 / 0,9
Nominal current 3~	17,3 V 3~
Nominal voltage 3~	400 V 3~
Nominal voltage 1~	230 V 1~
Prime power [PRP] kVA/kW 1~	6,9 / 6,2
Max. output [LTP] kVA/kW 1~	7,6 / 6,8
Prime power [PRP] kVA/kW 3~	12,0 / 9,6
Alternator	synchronous
Max. output [LTP] kVA/kW 3~	13,2 / 10,5
Fuel	Petrol
Tank capacity (litres)	16
Consumption l/h at 75% load	3,5
Running time (h) at 75% load	4,5
Start-up system	Electric start
Sound power level LWA db(A)	102
Weight ca. (kg)	137
Dimensions L x B x H (mm)	945 x 570 x 645
Shockproof sockets	1 x 230V CEE 16A, 1 x 400V CEE 16A